## **Piezoelectric Accelerometer**

### Model 2248, 2248M1

- Small Size
- Light Weight
- High Temperature Operation (+482°C)
- Radiation Hardened for Nuclear Environments
- Gas Turbine, Nuclear Applications

#### DESCRIPTION

The ENDEVCO<sup>®</sup> Model 2248 is a small piezoelectric accelerometer for shock and vibration measurement of structures subjected to very high temperatures. This device is capable of operation in nuclear environments during the presence of gamma and neutron radiation. It features a side 10–32 receptacle, with either flange (2248) or integral stud-mount (2248M1). The accelerometer is a self-generating device that requires no external power source for operation.

The 2248 features ENDEVCO's PIEZITE<sup>®</sup> Type P-14 sensing element in our patented ISOBASE<sup>®</sup> construction, to provide for flat charge temperature response over the range of -67°F to +900°F (-55°C to +482°C). ISOBASE construction provides mechanical isolation of base strain from the mounting surface. The unit is constructed using Inconel, and provides for hermeticity through welding and glass-to-metal fusion at the connector. Signal ground is connected to case.

ENDEVCO Signal Conditioner Model 2721B is recommended for use with this accelerometer. The 2771A Remote Charge Convertor is also compatible for applications using this high impedance accelerometer.









STANDARD TOLERANCE INCHES (MILLIMETERS) .XX = +/- .03 (.X = +/- .8) .XXX = +/- .010 (.XX = +/- .25)

10-32 UNE-2A THE

Actual size MODEL 2248M1





.200 (5.08)







#### ENDEVCO MODEL 2248 2248M1

### **ENDEVCO** MODEL 2248 2248M1

# **Piezoelectric Accelerometer**

#### **SPECIFICATIONS**

The following performance specifications conform to ISA-RP-37.2 (1964) and are typical values, referenced at +75°F (+24°C) and 100 Hz, unless otherwise noted. Calibration data, traceable to National Institute of Standards and Technology (NIST), is supplied.

DYNAMIC CHARACTERISTICS	Units		
CHARGE SENSITIVITY			
TYPICAL VALUES	pC/g	3.0	
MINIMUM	pC/g	2.4	
FREQUENCY RESPONSE		See Typical Amplitude Response	
RESONANCE FREQUENCY	kHz	25	
AMPLITUDE RESPONSE [2]			
±5%	Hz	1 to 6000	
±1dB, typical	Hz	.5 to 8000	
TEMPERATURE RESPONSE		See Typical Curve	
TRANSVERSE SENSITIVITY	%	≤ 5	
AMPLITUDE LINEARITY [3]	%	1	
Per 1000 g, 0 to 3000 g			
ELECTRICAL CHARACTERISTICS			
OUTPUT POLARITY		Acceleration directed into base of unit pro	oduces
		positive output	
RESISTANCE	GΩ	≥ 1	
At +900°F (+482°C) [2]	KΩ	≥ 100	
CAPACITANCE	pF	250	
GROUNDING		Signal return connected to case	
ENVIRONMENTAL CHARACTERISTICS			
TEMPERATURE RANGE		-65°F to +900°F (-54°C to +482°C)	
HUMIDITY		Hermetically sealed	
SINUSOIDAL VIBRATION LIMIT	g	500	
SHOCK LIMIT	q	3000	
BASE STRAIN SENSITIVITY	equiv. q pk/µ strain	0.0005	
RADIATION	1 01 1		
INTEGRATED GAMMA FLUX	rad	Up to 6.2 x 10 <sup>10</sup>	
INTEGRATED NEUTRON FLUX	N/cm <sup>2</sup>	Up to $3.7 \times 10^{18}$	
PHYSICAL CHARACTERISTICS			
DIMENSIONS		See Outline Drawing	
WEIGHT	gm (oz)	13 (0.46)	
CASE MATERIAL		Inconel	
CONNECTOR		10-32 coaxial connector	
MOUNTING TORQUE	lbf-in (Nm)	18 (2)	
CALIBRATION			
SUPPLIED:			
FREQUENCY RESPONSE	%	20 Hz to 8 000 kHz	
	dB	8 0000 kHz through resonance	
SENSITIVITY	pC/g	~	
MAXIMUM TRANSVERSE SENSITIVITY	%		
MOUNTED RESONANCE FREQUENCY	kHz		
CAPACITANCE	pF		
	P.		
ACCESSORIES			
Model EH 535 (2248) MOUNTING SCREWS,	6-32 X 2	3. Short duration shock pulses, such as those generate	d by metal-
Model 3075M6-120 (10 ft) CABLE ASSEMBLY, FC	)R > +260°C	to-metal impacts, may excite transducer resonance a	and cause
		A Maintain high levels of precision and accuracy using	Endevcols
OPTIONAL ACCESSORIES		factory calibration services Call Endevco's inside sa	ales force at
Model 3090C-120 (10 ft) CABLE ASSEMBLY, FOR < +260°C		800-982-6732 for recommended intervals, pricing an	d turn-
Model 33/5M6-36 CABLE ASSEMBLY aroun		around time for these services as well as for quotation	ons on our
P/N 33208 IN-LINE ADAPTER, HIGH TEMP		standard products.	
NOTES		北专汇海时间专用八司	
<ol> <li>Low-end response of the transducer is a function of its associated electronics.</li> <li>Because of low resistance at high temperatures, the signal condi- tioner must be capable of operating with the specified source resistance. Contact factory if you have any questions.</li> </ol>		北京汇润科贸有限公司	
		电话:+86 010 5601 8989	
		+ 86 010 5601 7979	
		佐百・+86 010 5895 7966	
		邮箱: <u>sales@aq315.com</u>	
		http://www.aq315.com	

Continued product improvement necessitates that Endevco reserve the right to modify these specifications without notice. Endevco maintains a program of constant surveillance over all products to ensure a high level of reliability. This program includes attention to reliability factors during product design, the support of stringent Quality Control requirements, and compulsory corrective action procedures. These measures, together with conservative specifications have made the name Endevco synonymous with reliability.

ENDEVCO CORPORATION, 30700 RANCHO VIEJO ROAD, SAN JUAN CAPISTRANO, CA 92675 USA (800) 982-6732 (949) 493-8181 fax (949) 661-7231